



Allowable Uses

- Manufactured/Mobile Homes
- Replacing existing 100A or less meter socket
- Non-critical commercial application

NOTES

- (1) Socket to be Underwriters Laboratory (UL) listed.
- (2) Connections for terminating service conductors shall be the lay-in type.
- (3) Service conduit to enter at point "A"
- (4) Meter shall be 4' - 5' 6" from finished grade.
- (5) Commercial application for non-critical loads, i.e. sprinkler control and gates. PNM will allow socket without bypass handle.
- (6) PNM does not permit a trough ahead of meter socket.
- (7) Metering and instrument cabinets shall not be used to house Customer-owned equipment, such as distribution panels or other equipment, nor used as a junction box/trough for the distribution of circuits.
- (8) Customer building numbers must be permanently painted on proper meter panels.

REFERENCES

- (1) See DS-4-6.0 120/240V Underground Service Pole
- (2) See DS-4-8.0 Overhead Permanent/Temporary Single-Phase or Temporary Three-Phase Service Pole
- (3) See DS-4-9.0 Underground Residential Customer-Owned Service
- (4) See DM-4-11.0 Maximum Available Fault Current

Approved Equipment		
Manufacturer	Item	Mfg Part #
Durham	100A OH/UG Ringless Socket	UTRS101B
Eaton	125A OH Ringless Socket	MBT48B125BTS
Eaton	125A OH Ringless Socket	UTRS101(*E
Eaton	125A OH Ringless Socket	1MP***
Milbank	125A OH/UG Ringless Socket	U7487-RL-TG
Milbank	125A OH/UG Ringless Socket	U7487-RL-TG-KK
Milbank	125A OH/UG Ringless Socket	U5101-XL-75
Square D	125A OH Ringless Socket	RC8165100CH

* Varies depending on hub size.

For ease of checking service without interruption, PNM will no longer allow ring meter sockets as of 12/01/2013.

120/240V 100-125A Customer Overhead or Underground
Single-Phase Meter Socket

MS-2-2.3