



Detail

NOTES

- (1) Level luminaire in accordance with manufacturer's instructions.
- (2) Minimum recommended mounting height is 28'.
- (3) Replacement for 135W LPS, 200W HPS, 250W HPS and 400W MV.

REFERENCES

- (1) See DS-2-11.0 Three-Phase Tangent and Small Angles
- (2) See DS-3-1.0 Secondary Tangent Structure
- (3) See DS-12-1.0 Lamp and Photo Control Identification Coding

Base Material List

| Item | Quan. | Description                    | Stock #     |
|------|-------|--------------------------------|-------------|
| A    | 1     | Medium LED Luminaire           | 0100-004656 |
| B    | 2     | Line Tap                       | DS-18-99.0  |
| C    | 1     | 6' Wood Pole Bracket           | 5975-260935 |
| G    | 1     | 5/8" MF Locknut                | 5310-153506 |
| H    | 2     | 1/2" x 4" Lag Screw            | 5305-147794 |
| J    | 1     | 2 1/4" Square Washer           | 5310-153571 |
| K    | 1     | 5/8" x _____ Machine Bolt      | DS-18-25.0  |
| L    | 1     | 5/8" Double Coil Spring Washer | 5310-163034 |

Material List with Photo Control

|   |    |                                 |             |
|---|----|---------------------------------|-------------|
| D | 1  | 105-305V Photo Electric Control | 0100-006641 |
| E | 8' | #8 THW White Wire               | 6145-000334 |
| F | 8' | #8 THW Black Wire               | 6145-000292 |

Material List without Photo Control

|   |     |                   |             |
|---|-----|-------------------|-------------|
| D | 1   | Shorting Cap      | 7000-192500 |
| E | 2'  | #8 THW White Wire | 6145-000334 |
| F | 16' | #8 THW Black Wire | 6145-000292 |