



NOTES

- (1) Bracket is to be grounded to neutral.
- (2) Adjust and turn twist-lock receptacle to the North. Level luminaire in accordance with manufacturer's instruction.
- (3) Replacement for 55W LPS, 70W HPS, 100W HPS and 175W MV.

REFERENCES

- (1) See DS-12-1.0 Lamp and Photo Control Identification Coding

Material List			
Item	Quan.	Description	Stock #
A	1	Small LED Luminaire	0100-004657
B	1	105-305V Long Life Photo Control	0100-006641
C	1	6' Wood Pole Steel Bracket	5975-260935
D	1	#4 Duplex Cable	6145-000995
E	2	5/8" x ___ Machine Bolt	DS-18-25.0
F	2	2 1/4" Square Washer	5310-153571
G	2	5/8" MF Locknut	5310-153506
H	1	5/8" Oval Eyenut	5310-154959
J	1	5/8" Cable Thimble	5975-265421
K	1	#4 ACSR Service Grip	5975-259135
L	2	Service Entrance Sleeve	5935-232867
M	8'	#8 THW Black Wire	6145-000292
N	8'	#8 THW White Wire	6145-000334
P	2	1/2" x 4" Lag Screw	5305-147794
Q	2	5/8" Double Coil Spring Washer	5310-163034