



NOTES

- (1) Pedestal constructed from 14 gauge steel with corrosion resistant finish.
- (2) Meter socket minimum rating 125A factory wired in separate wire way from terminal block to meter sockets.
- (3) Alternate: If plastic conduit is used in place of rigid, it must be encased in 2" of concrete from where it enters metal enclosure, to 18" below ground level.
- (4) Insulated stud terminal block or bus pads to accommodate PNM connections.
- (5) Pedestal bonding lug grounding conductor must be continuous to breaker panel grounding terminal.
- (6) Termination section to have removable rain tight cover with provision for padlocking. All other removable portions of termination section must be sealable.

For ease of checking service without interruption, PNM will no longer allow ring meter sockets as of 12/01/2013.

REFERENCES

- (1) See DM-4-11.0 Maximum Available Fault Currents

Maintenance Only